

Edge Airport France





Table des matières

Paramétrage impression OKI	
Paramétrage impression OKI	
Approbation	
Edge Airport France	



Paramétrage impression OKI

Paramétrage impression OKI

1. Cliquer dans Périphériques et imprimante.



Sélectionner l'imprimante OKI.

- 1. Cliquer sur l'onglet Print Server Properties (Propriétés du serveur).
- 2. La fenêtre Print Server Properties (Propriétés du serveur) s'ouvre.
- 3. Cliquer sur l'onglet Forms (Formulaire).

Print Server Pro	operties	<i>re</i>				×		
Forms Ports [Drivers Se	curity A	dvance	d				
Forms on:	BZVE1GT0	0601						
B5 (JIS) Rotated B5 (JIS) Transve B6 (JIS) B6 (JIS) Rotated	i erse				•	Delete Save Form		
Form name:	CUPP	T						
Create a new Define a new fo measurements	Create a new form Define a new form by editing the existing name and measurements. Then click Save Form							
-Form descript	ion (meası	urements	s) —					
Units:	Metri	c	\bigcirc	English				
Paper size:		Printer	area m	argins:				
Width:	22cm	Left:	[0,00cm	Тор:	0,00cm		
Height:	1cm	Right:	[0,00cm	Bottom:	0,00cm		
				ОК	Cancel	Apply		

- 1. Saisir le nom CUPPT dans le champ Form name (Nom du formulaire).
- 2. Cocher la case Create a new form (Créer un nouveau formulaire).
- 3. Cocher la case Metric.
- 4. Inscrire 22 dans le champ de saisie Width (largeur).
- 5. Saisir 1 dans le champ Height (hauteur).
- 6. Cliquer sur OK pour valider.
- 7. La fenêtre Print Server Properties (Propriétés du serveur) se ferme.

	7
	See what's printing
Ok 🗸	Set as default printer
	Printing preferences
	Printer properties
	Create shortcut
	Troubleshoot
	Remove device
	Properties



- 1. Faire un clic droit sur l'imprimante OKI.
- 2. Cliquer sur Printer properties (Propriétés de l'imprimante) dans le menu.
- 1. La fenêtre OKI properties s'ouvre.

ieneral	Sharing Ports	Advanced	Color Management
Security	Device Settings	Printer Commands	Font Selection
Generic	/ Text Only Device Sett	ings	
	n To Tray Assignment	2	
	Cont. Feed - No Break:	CUPPT	•
	Cut Sheet: <u>CUPPT</u>	CURRT	
i (Cont. Feed - With Break	: <u>CUPPT</u>	
		OK Can	Apply

Device settings (paramètres du périphérique).

- 3. Sélectionner le formulaire CUPP-T
- 1. Cliquer sur Apply pour appliquer.

Security	Device Se	ttings	Printer Commands	Font Se	election	
General	Sharing	Ports	Advanced	Color Mana	igement	
Δhwave a	wailable					
 Annays a Annays a 		0.00	- T	00.00		
O Available	e from	0:00	▼ 10	00:00	v	
Priority:	1					
	•					
Driver:	Generic / Te	xt Only		 New Dri 	ver	
Speed pr	int documents	so program	finishes printing fa	ctor		
Spool pr	int documents	so program	finishes printing fa	ster		
Spool pr Start	int documents printing after la	so program ast page is s	n finishes printing fa spooled	ster		
Spool pr Start Start	int documents printing after la	so program ast page is s diately	i finishes printing fa	ster		
Spool pr Start Start	int documents printing after la printing imme	so program ast page is s diately	n finishes printing fa pooled	ster		
 Spool pr Start Start Print dire 	int documents printing after la printing imme ectly to the prin	so program ast page is s diately nter	n finishes printing fa spooled	ster		
 Spool pr Start Start Print dire 	int documents printing after la printing imme ectly to the prin	so program ast page is s diately nter	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold mission 	int documents printing after la printing imme ectly to the prin smatched docu	so program ast page is s diately nter uments	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold mit Print spo 	int documents printing after la printing imme ectly to the prin smatched docu poled documen	so program ast page is s diately nter uments its first	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold mit Print spo Keep pri 	int documents printing after la printing imme ectly to the prin smatched docu poled documen nted document	so program ast page is s diately nter uments its first ts	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold minima Print spool Keep pri Keep pri 	int documents printing after la printing imme ectly to the prin smatched docu poled document nted document	so program ast page is s diately nter uments its first ts	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold mit Print spo Keep pri Enable a 	int documents printing after la printing imme ectly to the prin smatched docu poled document nted document dvanced printir	so program ast page is s diately ater uments ats first ats first ts ng features	n finishes printing fa	ster		
 Spool pr Start Start Print dire Hold minimative Print spool Keep print Keep print Enable a 	int documents printing after la printing imme ectly to the prin smatched docu poled documen nted document dvanced printir	so program ast page is s idiately iter iments its first its first ts p features Print P	rocessor	ster Separator Pac	Je	
 Spool pr Start Start Print dire Hold mis Print spo Keep pri Enable a Printing 	int documents printing after la printing imme ectly to the prin smatched docu ooled documen nted document dvanced printir	so program ast page is s idiately iter uments its first its ng features Print P	rocessor	ster Separator Pag	je	

Advanced (avancé).

- 3. Cliquer sur New Driver (Nouveau pilote).
- 1. La fenêtre Add Printer Driver Wizzard (Ajouter une imprimante) s'ouvre.





1. Cliquer sur Next (Suivant).

Add Printer Driver Wizard		×	J				
Printer Driver Selection The manufacturer and model determine which printer driver to use.							
Select the manufacturer and model of the printer driver to install. If the driver you want is not listed, click Have Disk to select the driver you want. If Windows Update is available, click it for more drivers for this processor and operating system.							
Manufacturer Generic Gestetner HP infotec KONICA MINOLITA This driver is digitally signed. Tell me why driver signing is	• •	Printers Generic / Text Only Generic IBM Graphics 9pin Generic IBM Graphics 9pin wide MS Publisher Color Printer MS Publisher Color Printer Windows Update Have Disk					
< Back Next > Cancel							

- 1. Cliquer sur Generic.
- 1. Cliquer sur Generic / Text Only.
- 2. Cliquer sur Next (Suivant).

			7	
			See what's printing	
	Ok	\checkmark	Set as default printer	
		_	Printing preferences	
			Printer properties	
			Create shortcut	
			Troubleshoot	
			Remove device	
1.			Properties	Faire u

Faire un clic droit sur l'imprimante OKI.

- 2. Cliquer sur Printing preferences (options d'impression).
- 3. La fenêtre OKI printing Preferences (Options d'impression) s'ouvre.

Layout Paper/Quality	
Orientation: Portrait Page Order:	
Front to Back Page Format Pages per Sheet 1 Draw Borders	
	Advanced
	OK Cancel Apply

l'onglet Layout (Disposition).

5. Sélectionner orientation Portrait.



🖶 OKI Printing Preference	es 🗾 📉
Layout Paper/Quality	
Tray Selection	
Paper Source:	Cont. Feed - No Break
	Advanced
	Advanced
	OK Cancel Apply

- Cliquer sur l'onglet Paper Quality (Papier / Qualité).
 Sélectionner le type de papier Cont. Feed No Break.
- 1. Cliquer sur Advanced (Avancée).
- 2. La fenêtre Paramètres avancées s'ouvre.

Generic / Text Only Advanced Options	x
Generic / Text Only Advanced Document Settings Paper/Output Copy Count: <u>1 Copy</u> Copy Count: <u>1 Copy</u> Advanced Printing Features: <u>Enabled</u> Pages per Sheet Layout: <u>Right then Down</u>	
OK Cancel	

- 1. Sélectionner le formulaire Cupp-T du format papier.
- 2. Cliquer sur OK pour valider.

Approbation

Fonction	Rédacteur	Vérificateur	Validateur
Prénom - Nom			
Signature			

From: http://edgeairport.alwaysdata.net/wiki/ - Documentation Embross (ex Edge Airport) Permanent link: http://edgeairport.alwaysdata.net/wiki/doku.php?id=manuel:installation:cuppt:oki&rev=1469525002 Last update: 26/07/2016 11:23



Edge Airport France

Airport Manager Solutions

Phone: +33 553 801 366

Service commercial : contact@edge-airport.com

Support technique : support@edge-airport.com

Edge Airport France SAS au capital de 150 000 €

RCS Bergerac 529 125 346 Les Lèches TVA : FR53529125346 / EORI : FR52912534600039

Tel: +33(0)553 801 366 contact@edge-airport.com www.edge-airport.com